

PE-130 downgrade to SATA 3G firmware SOP

Note: Program tool have to run it on real DOS environment, not Windows DOS mode

1. Please unzip RE1062.A13.zip and copy RE1062.A13 folder to C:\
2. Boot into DOS
3. Please into C:\RE1062.A13
4. Type "ahci.bat" to start update firmware
5. When screen shown "PASS : 1 FAIL : 0" that's mean update finish and successful.



```
C:\>cd re1062.a13
C:\RE1062.A13>ahci
C:\RE1062.A13>spiupd /U 803A_00.rom
DOS/4GW Protected Mode Run-time Version 1.97
Copyright (c) Rational Systems, Inc. 1990-1994
Asmedia ASM 2106B SPI ROM Update Utility - Version 1.70
Found 1 ASM 2106B controller

Update SPI flash ROM start:

Controller 0 : PCI bus 1, device 0 function 0 ...
Find a SPI flash ROM: GD25Q10, Capacity = 128 Kbytes
Update SPI flash ROM.....PASS

PASS : 1      FAIL : 0

C:\RE1062.A13>
C:\RE1062.A13>
```

Check new Firmware version

Firmware Version: 150910_80_3A_00

